

APPLICATION FOR UNITED STATES PATENT

by

DEREK JOHNSON AND MICHAEL HEUBEL

for

LOCATION DEFINED CONTROL OF CELLULAR SYSTEM

SHAW PITTMAN
2300 N Street NW
Washington, DC 20037
(202) 663-8000

Attorney Docket No.: BS01-053

LOCATION DEFINED CONTROL OF CELLULAR SYSTEM

FIELD OF THE INVENTION

[0001] The present invention generally relates to communications technology and, more particularly, to channel allocation in cell sites.

BACKGROUND OF THE INVENTION

[0002] Geographic reuse of frequencies, sometimes called "frequency reuse," is a distinguishing feature of cellular systems. Because a limited swath of the RF spectrum is available, frequencies are reused in order to provide a cellular system with an acceptable capacity. This is accomplished by breaking up the coverage area into a number of cells, or cell sites, each having a relatively low-powered transmitter. The transmitter has sufficient power to cover the cell site without interfering with other cell channels.

[0003] Frequencies can be reused by spacing "same channel" cells sufficiently far apart that the likelihood of interference is minimized. This permits two conversations to occur simultaneously on the same channel without conflict. Frequency reuse may be implemented using an architecture with a "reuse pattern." A reuse pattern is a building block of cells that is repeated in order to build up to the coverage area.

[0004] For example, in an $n=7$ cellular system, seven cells define the reuse pattern. For example, there may be a first cell A1 surrounded by six cells B1-G1. Placed adjacent to these first seven cells is a second set of cells with the same pattern, an A2 cell surrounded by six cells B2-G2. Additional sets of seven cells are added (A3-G3, A4-G4, and so forth) to build up to the entire coverage area.

[0005] The spacing between same channel cells is a function of the reuse pattern. In an $n=7$ system, at least two cells have to be traversed to arrive at a same channel cell (e.g., the

spacing between A1 and A2 or between C1 and C2). As n increases, spacing between same channel cells increases. As n decreases, spacing between same channel cells decreases.

[0006] Frequency reuse is one way to increase subscriber capacity in spite of the constraints imposed by the finite number of available channels. Frequency reuse has its limitations, however. For a given cell transmitter power and cell size, same channel cells can be spaced only so closely before interference becomes a problem.

[0007] Sometimes subscriber capacity can be increased through cell-splitting. In cell-splitting, each cell is split into subcells, with each subcell having its own transmitter. This permits greater frequency reuse, although the transmitter power of adjacent cells may have to be reduced to avoid interference. A significant drawback of cell-splitting is the cost of installing the new hardware. Additionally, many jurisdictions have regulations severely limiting cellular providers' ability to install new antennas.

[0008] Another disadvantage of cell-splitting is the increased complexity it creates in the cellular system. Furthermore, the likelihood of interference or dropped calls can increase. The burden on the Mobile Telephone Switching Office (MTSO), which coordinates these operations, thus increases significantly.

[0009] Another complication of cell-splitting is that as cell size decreases, the number and rate of "handoffs" increases. A handoff occurs when a cell phone moves from a first cell to a second cell. The MTSO controls handoffs, which entails commanding the cell phone to switch to a channel in the new cell. The connection between the cells and the MTSO is also switched so that the call is routed between the new cell and the MTSO. Thus, as the user moves between cells, the call is "handed off" from one cell to another.

[0010]

Handoffs are necessary to manage moving callers in a cellular-type system. However, handoffs can create certain difficulties. The number and rate of handoffs can impose a significant processing burden on the MTSO. Because multiple cell sites may transmit during the handoff process, the overall noise floor of the RF environment is raised. This reduces overall capacity of the system.

[0011]

When handoffs are mishandled, calls may be dropped or may be handed off to a less-than-optimum cell. If a call is handed off to a less-than-optimum cell, a handoff to a better cell may be required in a short period of time.

[0012]

As wireless carriers continue to grapple with frequency reuse and handoff issues, new challenges have arisen on other fronts. In order to address routing of emergency calls placed by cellular phones, the Federal Communications Commission (FCC) has issued a series of orders. These orders mandate that wireless providers begin supplying location information to public safety answering points ("PSAPs") in order to support an enhanced 911 (known as "E911") capability for portable wireless devices ("PWDs"). According to the FCC mandate, wireless providers must provide a Phase I capability in 2000, followed by a more robust Phase II capability in 2001. The FCC orders can be found at the web sites www.fcc.gov/Bureaus/Wireless/Orders/1996/fcc96264.txt and www.fcc.gov/Bureaus/Wireless/Orders/1999/fcc99245.txt.

[0013]

The Phase I capability requires that wireless carriers provide general location information. The general location information would locate the PWD to within a cell site or cell sector.

[0014]

In Phase II, the wireless providers must provide specific location information. The Phase II localization accuracy requirement depends on whether the localization technique

is network-based or handheld-based. For network-based localization solutions, the accuracy must be at least within 125 m at a one standard deviation probability (67%) and at least within 300 m at two standard deviations (95%). For handheld localization solutions, the accuracy must be at least within 50 m at one standard deviation and at least within 150 m at two standard deviations.

[0015] As a result of these FCC orders, a number of different techniques for localizing PWDs have been developed to support E911. Network-based solutions include TDOA (time difference of arrival), AOA (angle of arrival), TDOA/AOA in combination, and LPM (location pattern matching). Handheld-based solutions include GPS (global positioning system).

[0016] TDOA localization relies on the fact that a signal transmitted by a PWD can be received at multiple cell site transceivers at slightly different times. If the signal is received at three cell site transceivers, the differential timing information can be used to compute a position for the PWD.

[0017] AOA localization relies on the fact that a signal transmitted by a PWD is typically received at different angles at multiple cell site transceivers. Using direction-finding (compass) circuitry at the cell sites, the angle of arrival is computed at each cell site receiving the signal. By processing the angles of arrival, a position can be computed.

[0018] TDOA/AOA is a combined approach that relies on a synthesis of the TDOA and AOA techniques. In this approach, coordinate pairs may be computed for both the TDOA and AOA techniques. The two coordinate pairs may then be averaged or otherwise combined. On the other hand, this approach may provide for selecting one or the other technique in some circumstances.

[0019]

The location pattern matching (LPM) technique has been proposed for use in urban environments where tall buildings and other obstructions cause signal reflection and multipath phenomena. In LPM, the signal of the PWD is received at multiple cell site transceivers. The acoustic component of the signal is then analyzed and compared to a database of signal characteristics. The processing and database comparison permit signal anomalies such as multipath and echoes to be used to localize the PWD.

[0020]

SUMMARY OF THE INVENTION

[0021]

The present invention is directed to the control of a cellular system based on location information. According to one aspect of the invention, a system and method for controlling operations in a cellular system is disclosed. A serving cell or the mobile telephone switching office (MTSO) determines that a portable wireless device operating in a serving cell needs to be handed off (a "handoff"). This determination may be based on a diminishing signal strength and/or an increasing bit error rate of the transmission between the portable wireless device and the serving cell.

[0022]

The position of the portable wireless device is determined. The position may be determined based on any of a variety of well-known localization techniques, such as time difference of arrival (TDOA), angle of arrival (AOA), location pattern matching (LPM), or global positioning system (GPS). Other techniques for determining the location of the portable wireless device could be employed.

[0023]

A target cell is selected based on the position of the portable wireless device. Generally, the target cell is selected as the cell that is closest to the portable wireless device. However, other factors may be considered in selecting the target cell. For example, a position vector may be computed based on several measurements of the

location of the portable wireless device. A velocity vector may be computed based on several measurements of the location of the portable wireless device. Factors such as the position vector and/or the velocity vector may be assessed in selecting the target cell. Accordingly, the target cell may be selected to be a cell other than the cell closest to the current position of the portable wireless device.

[0024] Based on the target cell that is selected, the MTSO assigns the portable wireless device to the target cell and the transmission is handed off to the new cell.

[0025] The advantages of the present invention are numerous. Dropped handoffs may be reduced. The processing burden associated with handoffs may be reduced. The number and rate of handoffs may decrease. The background noise associated with the handoff process may decrease, thus increasing overall subscriber capacity. Frequency reuse can be increased, so that same channel cells can be spaced closer. Channels for adjacent cells can be spaced closer.

[0026] Accordingly, an object of the invention is to provide handoffs based at least in part on location information of a portable wireless device.

[0027] Another object of the invention is to provide handoffs in a manner such that the incidence of dropped handoffs is reduced.

[0028] Another object of the invention is to provide handoffs in a manner such that the number and rate of handoffs are reduced.

[0029] Another object of the invention is to provide handoffs in a manner such that the overall system capacity is increased.

[0030]

These and other objects of the present invention are described in greater detail in the following description of the invention, the appended drawings, and the attached claims.

BRIEF DESCRIPTION OF THE DRAWINGS

[0031]

Figure 1 provides a schematic block diagram of a system for performing location based handoffs according to an embodiment of the invention.

[0032]

Figure 2 is a diagram of a portion of an exemplary cellular system using a handoff to transfer a portable wireless device from one cell to another cell according to an embodiment of the invention.

[0033]

Figure 3 is a flow chart of a method according to an embodiment of the invention for handoff assignment based on location information.

[0034]

Figure 4 is a flow chart of a method for determining a target cell based on location information according to an embodiment of the invention.

[0035]

Figure 5 is a flow chart of a method according to an embodiment of the invention for performing handoffs based on location information.

DETAILED DESCRIPTION OF THE INVENTION

[0036]

Figure 1 is a block diagram, according to an embodiment of the invention, for a system 50 that uses location information for purposes of management and control of a cellular system. System 50 may be part of a larger system that includes an interface to the emergency services infrastructure of the public switched telephone network. The elements to the left of line A in Figure 1 relate to a cellular system, while those elements to the right of line A relate to the public switched telephone network, sometimes referred to as the Plain Old Telephone System or "POTS."

[0037]

Portable wireless devices 180 interface with cellular system 100 to place phone calls (or to transmit non-voice data) to other portable wireless devices 180 in cellular system 100 or to devices (e.g., land line telephones) in the public switched telephone network (PSTN). The portable wireless devices 180 could be any two-way device that permits the position of the device to be localized using suitable localization technologies, such as TDOA, AOA, TDOA/AOA, LPM, GPS, and any other existing or future technology for locating two-way portable devices.

[0038]

Portable wireless device 180 could be a portable cellular phone, a mobile phone, a two-way pager, a personal data assistant (PDA), or any other two-way transceiver type device that is portable and that permits localization. While portable wireless device 180 is preferably handheld, it could alternatively be installed in a vehicle.

[0039]

Portable wireless devices (PWDs) 180 interface with cellular system 100, which could be a digital or analog system. Both digital and analog cellular systems are well known in the art, including the cellular systems using TDMA (time division multiple access), CDMA (code division multiple access), FDMA (frequency division multiple access), so-called "mDiversity," or other types of transmissions. For example, cellular system 100 could be an Advanced Mobile Phone System (AMPS), a Digital Advanced Mobile Phone System (D-AMPS), a Portable Communication System (PCS), a global system for mobile communications (GSM), or other cellular-based communications system.

[0040]

Cellular system 100 includes a number of cell sites 135 (sometimes referred to as "base stations") having cell transceivers 140. Transmissions by portable wireless device 180 are generally received by a transceiver 140 in the "serving cell" (e.g., the cell site 135

most proximate to PWD 180) which forwards the transmission to the mobile telephone switching office (MTSO) 130. In reciprocal fashion, transmissions from other cellular phones, or from phones in the PTSN system, are transmitted from MTSO 130 to the transceiver 140 in the serving cell, which forwards the transmissions on to PWD 180. These transmissions may be FDMA, TDMA, CDMA, so-called "mDiversity," or any other suitable transmission type.

[0041]

The connection between MTSO 130 and cell sites 135 may comprise a microwave link, wire line, or other means for reliably connecting MTSO 130 and cell sites 135. Cell sites 135 may comprise a computer or controller (not shown) for performing processing operations, such as for measuring received signal strength or bit error rate in the transmission from PWD 180. MTSO 130 may comprise a computer or controller (not shown) for performing processing operations, such as for measuring a received signal strength or a bit error rate for PWD 180, for registering PWDs 180, for setting up calls, and for making handoffs.

[0042]

As used herein, "computer" is accorded its broadest meaning. A computer may comprise a personal computer, minicomputer, microcomputer, mainframe, processor, microprocessor, controller, microcontroller, and any other means for processing data.

[0043]

Referring to the right of line A on Figure 1, MTSO 130 in system 50 may interface with the POTS telephone system for both regular calls and emergency calls. For a regular call, MTSO 130 interfaces with local exchange carriers in order to complete calls to a called party 110. For emergency calls, MTSO 130 interfaces with an emergency services router (ESR) 115 (directly, or via PSTN 105) in order to route an emergency (e.g., 911) call to the proper public service answering point (PSAP) 120.

[0044]

In accordance with the well-known localization techniques previously discussed, system 50 is capable of identifying the location of a PWD 180. In one embodiment using the TDOA technique, differential timing information may be sent from MTSO 130 to location system 155, which computes a latitude/longitude (or X-Y) solution based on the differential timing information. In another embodiment using the AOA technique, the angle of arrival information may be sent from MTSO 130 to location system 155, which computes a latitude/longitude (or X-Y) solution based on the angle information. In yet another embodiment using the combined TDOA/AOA approach, differential timing and/or angle of arrival information is used to compute a location solution. In yet another embodiment using GPS technology, MTSO 130 collects GPS timing information from PWDs 180 equipped with GPS receivers. The GPS timing information is processed by location system 155 to compute a location. In yet another embodiment using GPS technology, MTSO 130 collects locations from PWDs 180 that perform their own location computations. According to other embodiments, system 50 provides location information using any other suitable existing or future technology for localization of two-way portable devices.

[0045]

The location information of PWDs 180 provided by system 50 can be made available to an automatic location identification (ALI) database 125 for use in routing personnel responding to emergency calls. In addition or alternatively, this location information can be used by MTSO 130 in its control and management of calls in cellular system 100. In particular, MTSO 130 can use this location information in making handoffs within cellular system 100.

[0046]

The general operation of an embodiment in accordance with exemplary system 50 in Figure 1 is as follows. Generally, as PWD 180 moves the signal strength of its link with a serving cell site 135 varies. As the signal strength of PWD 180's link with the serving cell site 135 decreases, and/or as the signal strength of PWD 180's link with other cell sites 135 increases, it may be desirable for the call to be handed off from the serving cell site 135 to one of the other cell sites 135. When MTSO 130 decides to make a handoff, it selects a "target cell" from a number of so-called "candidate cells." Rather than relying exclusively on signal strength to select the target cell, system 50 uses its location information to select the "target cell." By processing location information, the handoff process is improved.

[0047]

It should be understood that the block diagram of Figure 1 is functional in nature and is, therefore, but one example of how the overall system architecture may be designed. In particular, MTSO 130 and location system 155 are shown in Figure 1 to clearly illustrate the mobile switching operation of the one and localization operation of the other. However, MTSO 130 and location system 155 could easily be combined or further subdivided. For example, the localization processing performed by location system 155 could alternatively be performed by and integrated into MTSO 130.

[0048]

As noted above, a handoff is what occurs when a PWD 180 being served by a serving cell is switched or transferred to another cell, e.g., a target cell. Handoffs may occur when traffic on the serving cell exceeds its capacity. Most commonly, however, handoffs arise when a mobile PWD 180 begins to leave the effective operating range of the serving cell. The circumstances of an exemplary handoff are now described.

[0049]

Figure 2 is a diagram of an exemplary portion 200 of a cellular system using a handoff to transfer a portable wireless device from one cell to another cell. This exemplary portion 200 corresponds to an $n=7$ reuse pattern, wherein A1, A2 and A3; B1, B2 and B3; C1, C2 and C3; and so forth correspond to same channel cells. Same channel cells are cells with channel sets that include at least one common channel.

[0050]

For example, in Figure 2 at time t_1 the portable wireless device was being served by serving cell C1. At time t_1 , the portable wireless device is located at a position that could be defined by x_1, y_1 (x and y could correspond to Cartesian coordinates or to a longitude and latitude). At this time and position, the portable wireless device is operating on a channel in the channel set allocated to cell C1.

[0051]

Referring back to Figure 1, in an analog system such as the Advanced Mobile Phone System (AMPS), PWD 180's transmission is on a reverse voice channel received by the base station at cell C1 (one of seven cell sites 135 shown in Figure 1). Cell C1 forwards this transmission to MTSO 130 which, in turn, forwards it through PSTN 105 to called party 110. PWD 180 receives a transmission on a forward voice channel transmitted by the base station at cell C1. PWD 180 may also transmit or receive data on a control channel allocated to the channel set of cell C1. The control channel may be used for such operations as registration, paging, and call set-up.

[0052]

In a system other than AMPS, the transmissions between the portable wireless device and a base station are defined according to the protocols for those systems. For example, in a fully digital Time Division Multiple Access (TDMA) or Code Division Multiple Access (CDMA) system, the definition of a channel is different from that for an analog system such as AMPS. In particular, each portable wireless device may not be

assigned a dedicated, discrete frequency for carrying the transmission. However, the underlying principle is the same. While the portable wireless device is being served by serving cell C1, a channel from the channel set for cell C1 is used. When a handoff becomes appropriate, the portable wireless device is switched to a channel associated with one of the other cells.

[0053] Referring back to Figure 2, the portable wireless device is moving and at time t_2 , the portable wireless device is located at a new position that could be defined by x_2, y_2 at the edge (or the "boundary") of serving cell C1. As the portable wireless device approaches this boundary, the quality of the transmission degrades and a handoff is appropriate.

[0054] In the conventional approach, cellular system 100 (Figure 1) does not know that PWD 180 is located at x_2, y_2 , or even that it is at the edge of the serving cell C1. Cellular system 100 simply detects the decreasing quality of the transmission, and infers that a handoff should be made. According to this approach, measurements are made on the strength of PWD 180's link with several candidate cell sites. Based on these measurements, a target cell is selected and the handoff is made. In this conventional approach, the decision as to which cell to hand PWD 180 off to depends largely or entirely on measured signal strength (e.g., radio signal strength indication [RSSI] and/or bit error rate [BER]).

[0055] A drawback to this approach is that the call ("call" is defined broadly herein to include a voice type transmission, data type transmission, or other transmission between a PWD 180 and cellular system 100) may not be handed off to the best candidate cell. Referring to Figure 2, at time t_2 candidate cell F3 may have the best reception. For

example, candidate cell F3 may be reporting a signal strength and/or bit error rate that is marginally better than that at candidate cell E3. In the above approach, MTSO 130 hands the call off to candidate cell F3.

[0056]

However, in this exemplary scenario, it can be seen from Figure 2 that the geographically closest cell at time t_2 is candidate cell E3. Therefore, it may actually be the better choice to hand the call off to candidate cell E3. The marginally better link for candidate cell F3 may be a temporary signal anomaly. For example, tall buildings may be partially blocking the transmission link between PWD 180 and candidate cell E3, thus reducing the strength of the signal. If the call is handed off to candidate cell F3, another handoff to cell E3 might be required in a short period of time. In the worst case, the quality of the transmission between the portable wireless device and cell F3 might degrade so rapidly that the call is dropped altogether.

[0057]

Moreover, in Figure 2 it can be seen that at time t' the trajectory of the portable wireless unit changed. Even if candidate cell F3 has a better link (i.e., better signal strength and/or bit error rate) than candidate cell E3 at the point of handoff, the trajectory makes it likely that best target cell is E3, not F3. When the call is handed off to F3, the result may be that additional handoffs are required and/or a dropped call may result.

[0058]

In an improved approach according to an embodiment of the present invention, location information of the portable wireless device is employed in the handoff procedure. During the handoff procedure, a position of the portable wireless device is determined. The position may be determined using any of the localization technologies discussed previously. Any other reliable technique for locating a portable wireless device may be employed. The MTSO 130 (Figure 1) uses this position information in determining the

target cell. MTSO 130 may or may not consider signal strength and/or bit error rate information in making the determination.

[0059] Figure 3 is a flow chart of a method according to an embodiment of the invention for handoff assignment based on location information. In order to explain the invention, the method is described in connection with the structure of Figure 1. This is done only to explain the invention clearly and should not be considered to limit the disclosed method to the structure of Figure 1 or to any other structure.

[0060] The method starts at 305, at which point the PWD 180 is operating normally within a cell site 135. The handoff alert is generated at 315. The handoff alert may be generated by a serving cell 135 in cellular system 100 (Figure 1) based on the transmission received by serving cell 135 from PWD 180. The handoff alert could be generated by MTSO 130 based on the signal it receives from the serving cell 135 corresponding to the PWD 180. It is also possible that a handoff alert could be generated by PWD 180 based on the transmission it is receiving from the serving cell 135.

[0061] The handoff alert may be generated in response to the signal strength of the link between the PWD 180 and serving cell site 135 degrading below some level (e.g., the RSSI falls below an RSSI threshold and/or the BER rises above a BER threshold).

[0062] Alternatively or in addition, a handoff alert may be generated in response to the signal strength of a link between the PWD 180 and one of the other cell sites 135 increasing beyond some level (e.g., the RSSI rises above an RSSI threshold and/or the BER falls below a BER threshold). For example, in an AMPS system, MTSO 130 may command one or more other cells sites 135 to tune to the present voice channel occupied by PWD 130. These other cell sites may report back the measured signal strength and/or

bit error rate. These other cell sites may determine and report back whether the measured signal strength and/or bit error rate meets a threshold for making a handoff alert.

[0063] In a D-AMPS system, a mobile assisted handoff (MAHO) technique can be used. PWD 180 measures the received signal strength of signals in the TDMA transmission that correspond to one or more other cell sites 135. This information can be reported by PWD 180 back to MTSO 130 (Figure 1) for purposes of making a handoff alert.

[0064] In another embodiment, a handoff alert could be generated by considering both the signal strength of the link with the serving cell site 135 and the signal strength of a link with one of the other cell sites 135. For example, a handoff alert could be generated when it is determined that the link with the serving cell site 135 is weaker than the link with one of the other cell sites 135. This could be accomplished by measuring and comparing the respective RSSI's and/or BER's. The handoff alert could be generated in other manners.

[0065] In step 325, the position of the portable wireless device (e.g., PWD 180 of Figure 1) is determined. The position may be determined using any suitable localization technology, including those discussed previously.

[0066] In one embodiment, the position may be determined by retrieving previously stored location data for the portable wireless device. In other words, referring to Figure 1, MTSO 130 and/or location system 155 may be tracking the portable wireless device or determining its location on a regular basis, even before the handoff alert is generated. Thus, a very recent position can be used as the current position. Determining the position could also include using less recent positions to generate or extrapolate a position vector and/or to compute a velocity vector. A position vector and/or velocity vector can be used

to determine the direction in which and/or the rate at which the portable wireless device is moving.

[0067] Alternatively, or in addition to the above embodiment, the position is determined by performing a new location computation. For example, in response to the handoff alert, MTSO 130 and/or location system 155 in Figure 1 may compute a present location of PWD 180.

[0068] At 335, the position is processed to determine a target cell. The target cell, which is based at least in part on the position, can be determined in various manners. According to one embodiment, the target cell may be determined by selecting the cell closest to the position. According to another embodiment, the target cell may be determined by selecting the cell that corresponds to the projected trajectory or position vector of the portable wireless device. According to another embodiment, the target cell may be determined by selecting the cell based on the expected time PWD 180 will spend in the cell based on a velocity vector. According to another embodiment, the target cell may be determined by selecting the cell closest to the portable wireless device (or the cell that is selected based on a position vector and/or velocity vector) that also satisfies a minimum signal strength and/or maximum bit error rate requirement.

[0069] According to an embodiment, the target cell may be selected from an initial group of candidate target cells. For example, MTSO 130 may identify a set of candidate target cells for the serving cell that is handing off the call. The set of candidate cells may be those cells proximate to the serving cell. For example, if the serving cell is C1 in Figure 2, the candidate cells may be B1, G1, D1, A2, E3 and F3. A table of candidate handoff cells may be stored for each cell to account for geographic peculiarities or other variations

among cells in cellular system 100. The tables of candidate cells may be different for each cell in cellular system 100.

[0070] Alternatively or in addition, candidate target cells could be dynamically determined based on signal strength or bit error rate thresholds.

[0071] In yet another embodiment, step 335 for determining a target cell could comprise processing the position based on a stored geographic representation of the cellular coverage area. This geographic representation might include the various roads and highways in the coverage area. A position (e.g., an x, y Cartesian position or an x, y latitude/longitude position) could be correlated to the geographic representation to determine if PWD 180 is traversing a particular road or highway. This correlation could be performed by accessing a geographic information system (GIS) database or similar database for correlating positions to addresses and roads. Accordingly, a position vector or a velocity vector could be processed to determine a road or highway that PWD 180 appears to be traveling. Based on this determination, a particular target cell might be selected.

[0072] Coding of algorithms to perform the above logic is well within the skill of the ordinary artisan.

[0073] In step 345, the target cell is assigned so that the handoff can be effectuated. In one embodiment, this comprises MTSO 130 (Figure 1) issuing a command that causes PWD 180 to retune or transfer to the target cell. For example, in an analog AMPS system, MTSO 130 may issue a so-called "blank and burst" command on the existing voice channel that tells PWD 180 to retune to the new cell. This command may include the channel and a so-called supervisory audio tone (SAT) that allows PWD 180 to recognize the right channel.

[0074]

In cellular systems other than AMPS, such as fully digital TDMA or CDMA systems, MTSO 130 will issue a similar command to cause PWD 180 to change to the new cell. The details of such commands are well within the skill of the ordinary artisan.

[0075]

The method is complete at 350.

[0076]

Figure 4 is a flow diagram of part of a method for determining a target cell based on location information. In particular, step 335 for determining a target cell may include one or more of the steps of determining a position vector 410, determining a velocity vector 420, identifying candidate target cells 430, and evaluating the signal strength and/or bit error rate of candidate cells 440. Details of these steps were discussed above in connection with Figure 3.

[0077]

Figure 5 is a flow chart of a method according to another embodiment of the invention for performing handoffs based on location information. In this embodiment, location information is used to generate the handoff alert. Selecting a target cell may be based on the location information and/or signal strength. As with Figure 3, the exemplary method is explained by describing it in conjunction with certain structure from Figure 1. This is done in order to clearly explain the method, which should not be construed as being limited to that or any other structure.

[0078]

According to Figure 5, the method begins at 505. The position of a portable wireless device 180 is determined at 515. Determination of the position may be accomplished using any of the approaches described above for step 325 of Figure 3. Determination of the position may include generating a position vector and/or a velocity vector.

[0079]

A handoff alert is generated at 525 based on the position. For example, MTSO 130 (Figure 1) may generate the handoff alert by determining that the position of PWD 180 is near or approaching the boundary of the serving cell. MSTO 130 may make this determination based on a present position of PWD 130. MSTO 130 may make this determination based on a position vector and/or a velocity vector. In another embodiment, the serving cell 135 may generate the handoff alert.

[0080]

At 535, the position and/or the signal strength is processed in order to determine a target cell. According to a first embodiment, the position is processed to determine which is the best target cell. The best target cell may be the cell that is closest to PWD 180 or it may be the cell that corresponds best to PWD 180's position vector and/or velocity vector. The best target cell may be selected from a group of candidate cells, as described above for Figure 3. In a second embodiment, the target cell is selected by measuring the signal strength of a link between PWD 180 and a candidate cell(s). A candidate cell meeting a signal strength threshold (e.g., RSSI and/or BER) may be selected as the target cell. Alternatively, the candidate cell with the best signal strength may be selected. In a third embodiment, both the position and signal strength are processed in order to determine the target cell.

[0081]

At 545, the target cell is assigned. Assignment of the target cell was discussed above in connection with step 345 of Figure 3. The method is complete at 550.

[0082]

Having described the use of location information in the handoff procedure, it can be appreciated that numerous advantages result therefrom. The number and rate of handoffs can be reduced because calls are handed off to the best cell. The processing load on the cellular system can be reduced. The incidence of dropped calls may decrease. The overall

capacity of the system can be increased because frequency reuse can increase. Thus, same channel cells may be spaced closer in position. Channels on directly adjacent cells may be spaced closer in frequency. Because the handoff process is simplified, transmissions by fewer candidate cells may be required during the handoff process. Thus, interference noise (e.g., referring to the signal-to-noise ratio based on the so-called $C/I+n$ ratio, where C = strength of the carrier, n = background noise, and I = interference from other cells) may decrease. This may result in an improved signal strength in the link between a portable wireless device and a serving cell, providing more net bandwidth corresponding to greater capacity.

[0083]

The foregoing disclosure of the preferred embodiments of the present invention has been presented for purposes of illustration and description. It is not intended to be exhaustive or to limit the invention to the precise forms disclosed. Many variations and modifications of the embodiments described herein will be obvious to one of ordinary skill in the art in light of the above disclosure. The scope of the invention is to be defined only by the claims appended hereto, and by their equivalents.

[0084]

Further, in describing representative embodiments of the present invention, the specification may have presented the method and/or process of the present invention as a particular sequence of steps. However, to the extent that the method or process does not rely on the particular order of steps set forth herein, the method or process should not be limited to the particular sequence of steps described. As one of ordinary skill in the art would appreciate, other sequences of steps may be possible. Therefore, the particular order of the steps set forth in the specification should not be construed as limitations on the claims. In addition, the claims directed to the method and/or process of the present

invention should not be limited to the performance of their steps in the order written, and one skilled in the art can readily appreciate that the sequences may be varied and still remain within the spirit and scope of the present invention.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
2229
2230
2231
2232
2233
2234
2235
2236
2237